

MENU / MENÜ / MENÚ

Mode	Programming	Description
d001	001- 512	DMX512 address setting -6-channel mode
A001	001- 512	DMX512 address setting -10-channel mode
S-SL	SL / FA	DMX512 dimming speed setting SL: slow dimming; FA: fast dimming
d-Ho	Ho / oF	DMX signal loss processing mode setting: Ho: keep the last DMX signal state; oF: Turn off all LEDs
Iron	ON-OFF	IR remote control
r255	000 - 255	Red dimming , from dark to bright
G255	000 - 255	Green dimming , from dark to bright
b255	000 - 255	Blue dimming , from dark to bright
u255	000 - 255	White dimming , from dark to bright
Y255	000 - 255	Amber dimming , from dark to bright
P255	000 - 255	UV dimming , from dark to bright
I255	000-255	IR remote control brightness
F000	000 - 255	Strobe, speed from slow to fast
CL01	000-255	15 kinds static colour selectable
CC15	00- 15	Colour jumping, speed from slow to fast
DE15	00- 15	Colour Gradual change, speed from slow to fast
CP15	00- 15	Colour Pulse change, speed from slow to fast
SU15	00- 15	Sound control
t 30	00-99	Current temperature display when not used the display will show : t ---

DMX CHANNELS / DMX KANALEN / DMX-KANÄLE / CANALES DMX / CANAUX DMX

6 Channels

Channel	Function	Value	Description
1	Colour	000-255	Red dimmer from dark to bright
2		000-255	Green dimmer from dark to bright
3		000-255	Blue dimmer from dark to bright
4		000-255	White dimmer from dark to bright
5		000-255	Amber dimmer from dark to bright
6		000-255	UV dimmer from dark to bright

10 Channels

Channel	Function	Value	Description
1	Master dimmer	000-255	From dark to bright
2	Colour	000-255	Red dimmer from dark to bright
3		000-255	Green dimmer from dark to bright
4		000-255	Blue dimmer from dark to bright
5		000-255	White dimmer from dark to bright
6		000-255	Amber dimmer from dark to bright
7		000-255	UV dimmer from dark to bright
8	Strobe	000-255	Strobe from slow to fast
9	Program	000-050	No function
		051-100	15 kinds of colour output controlled by channel10
		101-150	Colour jumping
		151-200	Colour gradual change
		201-250	Colour pulse change
10	Program speed	000-255	Function speed from slow to fast